

AquaMaster 3 FET200

Electromagnetic flowmeter transmitter



The smart solution for remote applications

Measurement made easy

—
AquaMaster 3
FET200
Electromagnetic
flowmeter
transmitter

Introduction

AquaMaster 3™ is a range of high performance electromagnetic flowmeters for the measurement of electrically-conductive fluids and is normally supplied as factory-configured, calibrated systems.

This User Guide provides end-user details for AquaMaster 3 close-coupled and remote transmitters.

When the meter is taken out of storage and installed for first use, remove the protective label (if fitted) from the front to enable light to activate the unit.

If the meter is not powered, connect any batteries or external supply as detailed in this manual.

For more information

Further publications are available for free download from www.abb.com/flow or by scanning this code:



Search for or click on

Data Sheet [DS/FEF200/FEV200-EN](http://www.abb.com/flow/DS/FEF200/FEV200-EN)
AquaMaster3
Electromagnetic flowmeter

Data Sheet [DS/AMAS-EN](http://www.abb.com/flow/DS/AMAS-EN)
AquaMaster
Electronic water meter

Related documents

AquaMaster 3 flowmeter (FEA200)

Search for or click on

Programming Guide
AquaMaster 3
Electromagnetic flowmeter

[COI/FET2XX-EN](#)

IMPORTANT NOTE

For devices manufactured before February 2022, kindly refer to earlier revision of the user guide (Revision M) –

[OI/FET200-EN Revision M](#)

Contents

1	Safety and Security	3
1.1	Electrical Safety	3
1.2	Symbols	3
1.3	Security	3
1.4	Health & Safety	4
1.4.1	Battery Hazard, Handling, Shipping and Recycling / Disposal	5
1.5	Waste Electrical and Electronic Equipment (WEEE)	5
2	Mechanical Installation	6
2.1	Installation Conditions	6
2.2	Fitting the Vandal-Resistant Housing (Integral Transmitters Only)	8
2.3	Dimensions	9
2.3.1	Remote- and Close-Coupled Transmitter	9
2.3.2	Integral Transmitter and Vandal-Resistant Housing	10
2.3.3	External Battery Pack	10
2.4	GSM-Equipped Transmitters	11
2.4.1	GSM Antenna Installation	11
2.4.2	Connecting a Remote Antenna	13
2.4.3	Installing a SIM Card	13
3	Electrical Installation	15
3.1	Grounding	15
3.2	Connections	18
3.2.1	AquaMaster3 Sensor Connections (Remote or Close-Coupled only)	18
3.3	Input / Output Connections	19
3.3.1	Frequency Outputs	19
3.3.2	Alarm Interface	19
3.3.3	Input / Output Connections	20
3.3.4	RS232 Local Computer Connection	21
3.3.5	Pressure Transducer (Optional)	22
3.4	Power Supply Connections	23
3.4.1	Fitting / Replacing Internal Batteries (Integral Transmitters Only)	23
3.4.2	External Battery Power Supply	25
3.4.3	Mains Power Supply	25
3.4.4	Renewable Energy Supply	26
4	Start-Up and Operation	27
4.1	Start-up	27
4.2	Display Activation	28
4.3	Display Information	28
4.4	Servicing Plugs and Sockets	28
4.4.1	Service Intervals	28
4.4.2	Equipment Required	29
4.4.3	Preparation	29
4.4.4	Disconnection	29
4.4.5	Order of Treatment	30
4.4.6	Stage 1 – Oxide Removal and Cleaning	30
4.4.7	Stage 2 – Oxide Prevention	31
4.4.8	Completion tasks	31
5	Specification	32

Appendix A – GSM-Equipped Units, Safety Precautions37

Appendix B Accessories / Spares Kits38

 B.1 Common accessories38

 B.2 Adapter Cable / Upgrade Kits39

1 Safety and Security

Information in this manual is intended only to assist our customers in the efficient operation of our equipment. Use of this manual for any other purpose is specifically prohibited and its contents are not to be reproduced in full or part without prior approval of the Technical Publications Department.









1.1 Electrical Safety

This equipment complies with the requirements of CEI/IEC 61010-1:2010 'Safety Requirements for Electrical Equipment for Measurement, Control and Laboratory Use' and complies with US NEC 500 and Occupational Safety & Health Administration.

If the equipment is used in a manner NOT specified by the Company, the protection provided by the equipment may be impaired.

1.2 Symbols

One or more of the following symbols may appear on the equipment labelling:

	Warning – Refer to the manual for instructions		Direct current supply only
	Caution – Risk of electric shock		Alternating current supply only
	Protective earth (ground) terminal		Both direct and alternating current supply
	Earth (ground) terminal		The equipment is protected through double insulation

1.3 Security

Important (note)

This product is designed to be connected to and to communicate information and data via a network interface. It is your sole responsibility to provide and continuously ensure a secure connection between the product and your network or any other net- work (as the case may be). You shall establish and maintain any appropriate measures (such as but not limited to the installation of firewalls, application of authentication measures, encryption of data and installation of antivirus programs) to protect the product, the network, its system and the interface against any kind of security breaches, unauthorized access, interference, intrusion, leakage and/or theft of data or information. ABB Limited and its affiliates are not liable for damages and/or losses related to such security breaches, any unauthorized access, interference, intrusion, leakage and/or theft of data or information.

1.4 Health & Safety

Health and Safety

To ensure that our products are safe and without risk to health, the following points must be noted:

- The relevant sections of these instructions must be read carefully before proceeding.
- Warning labels on containers and packages must be observed.
- Installation, operation, maintenance and servicing must only be carried out by suitably trained personnel and in accordance with the information given.
- Normal safety precautions must be taken to avoid the possibility of an accident occurring when operating in conditions of high pressure and / or temperature.
- Chemicals must be stored away from heat, protected from temperature extremes and powders kept dry. Normal safe handling procedures must be used.
- When disposing of chemicals ensure that no two chemicals are mixed.

Safety advice concerning the use of the equipment described in this manual or any relevant hazard data sheets (where applicable) may be obtained from the Company contact details on the back cover, together with servicing and spares information.

Warning.

- Installation and maintenance must be carried out only by suitably trained personnel.
- Read all relevant sections of this manual before selecting a location.
- The safety requirements of this equipment, any associated equipment and the local environment must be taken into consideration during installation.
- Install and use this equipment in accordance with relevant national and local standards.
- Specific safety precautions apply to the use of the GSM engine that forms part of the GSM-equipped version of this product. If the unit purchased has GSM-capability, read Appendix A on page 37 before selecting a location.

1.4.1 Battery Hazard, Handling, Shipping and Recycling / Disposal

Warning.

AquaMaster is available with choice of battery technologies; Manganese Alkaline (part no WABC2100) or Lithium Thionyl Chloride (part no WABC2101 or WABC2102 or 'D' size cell). The following warnings must be observed:

- To ensure safety and correct operation, use only the batteries / battery packs listed in this manual or approved by ABB.
- Incorrect use or operation of batteries / battery packs may result in potentially serious hazards to personnel.
- DO NOT expose batteries / battery packs to fire or temperatures above 85 °C (185 °F) and DO NOT crush or puncture – they may leak, explode or rupture violently.
- DO NOT ship or transport the AquaMaster 3 Integral form with Lithium cells fitted unless the following instruction is complied with:
 - **Transporting Lithium Batteries / Battery Packs or product containing Lithium batteries / cells.** These are classified in 'category UN3091 – Class 9' of the UN list of hazardous materials. The transport of such cells / battery packs must conform to the prevailing rules that are specific to the means of transport used, both in terms of packing, identification and accompanying documents. The carrier must always be informed of the contents. A warning label 'Hazardous Label for Class 9 – Miscellaneous Hazardous Goods' must be attached to the packing and remain visible on the outside of the package.
- DO NOT dispose of depleted or partially depleted batteries. They MUST be recycled in accordance with local regulations (for example, sent to a specialist recycling centre that handles such batteries). The battery or battery pack must be packed, labelled and transported in accordance with the regulations. Ensure the battery cannot be short circuited.
- Recycling in Europe must be in accordance with 91/157/EEC and 93/86/EEC Directives.
- Damaged, leaking or overheated batteries require urgent specialist handling and treatment. Immediately evacuate all personnel from the area and seek professional assistance.

1.5 Waste Electrical and Electronic Equipment (WEEE)

WEEE EU Directives 2002/96/EC and 2003/108/EC cover disposal and recycling of electronic equipment at the end of life for reasons of environmental protection. Not all products are covered by the categories in this directive.



For industrial installations, portable equipment is included. This means that when the AquaMaster transmitter is used with a portable AquaProbe sensor, it is included in directive's scope and has the WEEE symbol (left) on its data label. Therefore, at the end of life, contact the supplier for specialist waste recycling. It must not be disposed of as municipal waste.

Permanent Industrial installations are not designated within this directive for recycling. At the point of supply the intended use is not always known, so the WEEE symbol is included on all remote forms of the AquaMaster transmitter.

2 Mechanical Installation

2.1 Installation Conditions




Fig. 2.1 Siting




Fig. 2.2 Within Temperature Limits




Fig. 2.3 Shade




Fig. 2.4 Vibration




Fig. 2.5 Spillage




Fig. 2.6 Within Environmental Rating




Fig. 2.7 Access to Transmitter




Fig. 2.8 Pressure Transducer – Protect from Frost

2.2 Fitting the Vandal-Resistant Housing (Integral Transmitters Only)

Referring to Fig. 2.9:

1. Slide cover (A) over transmitter.
2. Insert bottom plate (B) ensuring clips (C) enter lugs (D).
3. Secure with lock (E).




Fig. 2.9 Fitting Anti-Vandal Housing

2.3 Dimensions

2.3.1 Remote- and Close-Coupled Transmitter




Fig. 2.10 AquaMaster3 Dimensions

2.3.2 Integral Transmitter and Vandal-Resistant Housing




Fig. 2.11 Integral Transmitter Dimensions




Fig. 2.12 Vandal-resistant housing dimensions

2.3.3 External Battery Pack




Fig. 2.13 AquaMaster3 Battery Pack Dimensions

2.4 GSM-Equipped Transmitters

2.4.1 GSM Antenna Installation

Before deciding on an antenna mounting location, check that the local signal strength for the chosen mobile phone network is satisfactory. Use the GSM-equipped transmitter's integral signal strength test facility to establish signal strength. Refer to Programming Guide (COI/FET2XX-EN), Section 5.

If a GSM-equipped transmitter is not available, a standard mobile phone on the same network, positioned as close as possible to the intended location, gives a good indication of local signal strength. For GSM and logger download services, a minimum of 2 visible signal strength indicator 'bars' are recommended. For SMS text, a minimum of 1 visible signal strength indicator 'bar' is recommended.

The following must also be observed when deciding on the antenna mounting location:

- For best results, mount the antenna as high above local ground level as possible.
- If the antenna must be mounted below ground, achieve optimum results by ensuring:
 - there is a strong mobile phone network signal at ground level
 - the antenna, mounted 50 mm (2 in.) below the chamber cover, must be plastic – see Fig. 2.14, page 12
- Ensure the antenna does not become submerged under water – see Fig. 2.14, page 12.
- Metallic enclosures seriously degrade the signal. If an enclosure is used it must be non-metallic.
- Do not mount the antenna closer than 50 mm (2 in.) to any solid wall or surface – see Fig. 2.15, page 12.
- Do not mount the antenna beneath a solid surface (for example, metal cover, floor / ceiling).




Fig. 2.14 GSM Antenna Installation




Fig. 2.15 GSM Antenna Installation

2.4.2 Connecting a Remote Antenna

Referring to Fig. 2.16:

1. Remove the cover (A) from the socket on top of the transmitter.
2. Gently push the antenna plug (B) into the socket, then twist the screw ring clockwise until locked.




Fig. 2.16 Connecting a Remote Antenna

2.4.3 Installing a SIM Card

Referring to Fig. 2.17:

Note. Step 1 is applicable only to remote- and close-coupled transmitters.

1. Remove the transmitter from its mounting point.

Note. Step 2 is applicable only to integral transmitters.

2. Remove 4 x 4 mm Hex fixing screws (A) and remove the transmitter.
3. Use water to wash off any loose dirt from the case and dry the area around the SIM card cover.
4. On the back of the transmitter, unscrew and remove cover (B) protecting SIM card holder (C).
5. If the SIM card is being changed, ensure the GSM Engine is off before removing the card by reading >368 (see COI/FET2XX-EN) and ensuring the status reported is *Off*.
6. Carefully lift the right-hand edge of holder (C) outwards.

7. Slide SIM card (D) into holder (C), contact side down and bevelled edge to the top-right.
8. Close holder (C) until it clicks into place and refit cover (B).
9. Screw cover (B) firmly in place.

Note. Step 10 is applicable only to remote- and close-coupled transmitters.

10. Refit the transmitter to its mounting point.

Note. Step 11 is applicable only to integral transmitters.

11. Position the transmitter on the integral mount and secure with 4 x 4 mm Hex fixing screws (A). Tighten the screws to 4Nm.




Fig. 2.17 Installing a SIM Card

3 Electrical Installation

3.1 Grounding

Note. The grounding arrangements shown in Figs 3.1 to 3.3 are applicable to:

- new installations **ONLY**
- both cathodic and non-cathodic protected installations




Fig. 3.1 AquaMaster3 Transmitter Mounted in a Chamber – Flanged Sensor




Fig. 3.2 AquaMaster3 Transmitter Mounted in a Cabinet – Flanged Sensor




Fig. 3.3 AquaMaster3 Transmitter Mounted in a Cabinet – Probe Sensor

Note. The grounding arrangement shown in Fig. 3.4 is applicable only to:

- cathodic protected installations
- installations where E_2 and E_3 are different to E_1

Caution. Incorrect installation will result in fault currents flowing through the meter resulting in unstable readings.




Fig. 3.4 Cathodic Protected Installations with Different Cathodic Potential Generators

3.2 Connections

3.2.1 AquaMaster3 Sensor Connections (Remote or Close-Coupled only)

Referring to Fig. 3.5:

1. Remove the screwed cap (A) on the sensor connector.
2. Gently push the sensor plug (B) into the socket and rotate it until it engages, then tighten the locking ring.

Note. If the sensor cable is terminated with fly leads, connection is via a sensor cable adapter box (part number WABC2035 available separately).




Fig. 3.5 Sensor Connections

3.3 Input / Output Connections

Caution.

- Refer to the Specification, Section 5, page 32 for input / output ratings.
- Inductive loads must be suppressed or clamped to limit voltage swings.
- Operation of outputs is programmable – see Programming Guide (COI/FET2XX-EN) for details.
- External isolators are not normally required as the pulse and alarm circuit is electrically-separated from all other AquaMaster3 connections.
- Capacitive loads must be inrush current limited.
- Fully-floating pulse outputs may be subject to static damage, for example connecting to a floating datalogger, unless 'COM' is operated within its galvanic isolation range (± 35 V) from earth.

3.3.1 Frequency Outputs




Fig. 3.6 Frequency Output Connections

Note. Outputs 1 and 2 are not polarity-sensitive. The common connection for these outputs is designated 'COM'.

3.3.2 Alarm Interface




Fig. 3.7 Alarm Output Connections

Note. Output 3 is not polarity sensitive. The common connection for these outputs is designated 'COM'.

3.3.3 Input / Output Connections




Fig. 3.8 Input / Output Connectors

Pin	Signal	Function	Color (Output Cable)
A	Not used	Not used	Violet
B	Not used	Not used	Blue
C	O/P COM	Output Common	Yellow
D	O/P2	Reverse Pulses or Direction Indicator	Red
E	O/P3	Alarm Output	Brown
F	O/P1	Forward Pulses or Forward & Reverse Pulses	Orange
G	Not used	Not used	Screen

Table 3.1 Connector Input / Output Connections

3.3.4 RS232 Local Computer Connection




Fig. 3.9 RS232 Local Computer Connections

Note.

- A USB Comms lead driver is required when using WEBC2100 – download from www.ftdichip.com/FTDrivers.htm
- On battery or renewable energy versions, do not leave an RS232 connection plugged in or wired with voltages applied unnecessarily. Such voltages result in far higher power consumption from the battery or backup source, limiting battery / backup life.

3.3.5 Pressure Transducer (Optional)

Optional pressure transducer cables are available for a range of pressures and cable lengths.




Fig. 3.10 Optional Pressure Transducer Connector

Caution. Use only the pressure transducer supplied with the transmitter. Use of other pressure transducers requires alteration of the pressure span and zero factors in the transmitter.

3.4 Power Supply Connections

AquaMaster3 has 4 power supply options:

- Internal batteries (integral transmitters only) – see Section 3.4.1 (following)
- External battery pack – see Section 3.4.2, page 25
- Mains power – see Section 3.4.3, page 25
- Renewable energy – see Section 3.4.4, page 26

Warning.

- Disconnect the supply from any cables being terminated on the transmitter.
- Electrical installation and earthing (grounding) must be in accordance with relevant national and local standards.

Note. Power supply connections / earthing arrangements are identical for cathodically-protected remote transmitter systems. For cathodically-protected integral transmitter systems, follow cathodic installation practices.

3.4.1 Fitting / Replacing Internal Batteries (Integral Transmitters Only)

Caution.

- Observe all warnings in Section 1.4.1, page 5.
- Never remove lid when water level around the flowmeter is close to enclosure lid.
- Use 3.6 V Lithium cells only
- **DO NOT** use spirally wound cells.
- Ensure correct polarity (all cells must face upwards)
- Do not mix old and new cells
- Use cells from a single manufacturer
- Use only batteries of the correct type, as listed in Appendix B.1, page 38.

Referring to Fig. 3.11:

1. Remove enclosure lid (A).
2. Remove and discard silica gel bag.
3. Disconnect battery connector (B).
4. Carefully remove battery pack (C) from enclosure.
5. Carefully remove 3 cells (D) in turn from the top level of the pack.
6. Carefully remove 3 cells (E) in turn from the bottom level of the pack.
7. Fit 3 new cells to the bottom level of the pack, ensuring the correct polarity, as shown in Fig. 3.11, page 24.
8. Fit 3 new cells to the top level of the pack.
9. Carefully refit battery pack (C) to enclosure.
10. Reconnect battery connector (B).
11. Place new silica gel bag on top of battery pack.
12. Ensuring O-ring seal and O-ring groove is clean, refit enclosure lid (A) and tighten finger-tight.




Fig. 3.11 Internal Battery Pack (Integral Transmitters Only)

3.4.2 External Battery Power Supply

Note. Before making connections, check the Data label to confirm power supply requirements. AquaMaster3 can be powered from Explorer-style battery packs fitted with the MIL plastic style plug. The Explorer battery capacity is $\frac{6}{7}$ of published life.

AquaMaster3 can be supplied with an optional battery pack.




Fig. 3.12 Connecting a Battery Supply

3.4.3 Mains Power Supply

Note. Before making connections, check the Data label to confirm power supply requirements.

Mains power requirements:

- 110 to 240 V AC, 50 / 60 Hz @ <3 VA
- Cable length 3 m (9.8 ft.)
- Protected by a fused isolator, rating – mains, anti-surge 3 A.

Make connections as shown in Fig. 3.13.




Fig. 3.13 Connecting a Mains Power Supply

3.4.4 Renewable Energy Supply

Note.

- Before making connections, check the Data label to confirm power supply requirements.
- An output regulator can be omitted if the off load-voltage is below V in max.
- Renewable energy generators do not operate at maximum capacity, for example, low wind speeds, coating of the solar panel with dust and wildlife droppings and short daylight periods in winter. For these reasons, in some installations, generators with a capacity greater than the specified 5 W minimum should be used. Contact ABB for a technical note, giving guidance on the selection of suitably sized generators for AquaMaster3.

Renewable energy supply requirements:

- Input 12 V (nominal)
- V in max. 22 V DC
- V in min. 6 V DC
- Solar panel or wind generator 5 W or greater




Fig. 3.14 Connecting a Renewable Energy Supply

4 Start-Up and Operation

Warning.

- Observe all battery and other warnings in Section 1.4, page 4.
- Operation at extremes of temperature significantly shortens the battery capacity and life – see Specification, page 32.

4.1 Start-up

To start the AquaMaster3 for the first time:

1. Connect the external power source; mains / battery or renewable power source – see Section 3.4, page 23.
2. Remove transportation label.
3. Cover the display area for a few seconds.
4. Uncover the display area. The display is activated, the AquaMaster3 performs a self-test and begins communication with the sensor.

A successful connection is indicated by the message 'Pass' in the display window and normal flowmeter operation commences.

Notes.

- If the display shows 'Err 1', check the sensor wiring. If the fault is rectified, the transmitter restarts automatically.
- If the display shows 'Err 2' or 'Err 3', contact ABB.

4.2 Display Activation

To activate the display during normal operation:

- 1. Cover the display area for a few seconds.
- 2. Uncover the display area. The display is activated and the AquaMaster3 cycles through the programmed set of display measurements.

Note. To use local or remote serial communications, for instructions on how to alter the displayed set of measurements and for meter setup, refer to COI/FET2XX-EN.

4.3 Display Information




Fig. 4.1 AquaMaster3 Display Information

4.4 Servicing Plugs and Sockets

To ensure long and reliable service life for the plugs and sockets on AquaMaster3 Flow Transmitters, ABB recommend regular treatment of the gold connector pins.




Fig. 4.2 Transmitter Sockets (MIL Style)

4.4.1 Service Intervals

Treat all connectors:

- at 3-year intervals
- when the battery pack is changed
- when the installation is visited for other reasons (such as CalMaster 2 Verification)

4.4.2 Equipment Required

Cleaners are available from your local ABB representative. To purchase supplies directly or for local distributor details please go to the following website:

<http://store.caig.com/>

Material details are:

Description	Part No.
DeoxIT® – Contact Cleaner & Rejuvenator DeoxIT® – Mini-spray, 5 % solution, flushing action, 14 g (Applications = 150 approx.)	D5MS-15
DeoxIT® GOLD – Contact Enhancer, conditioner & Protector DeoxIT® GOLD G5 Mini Spray 5 % solution, 14 g, flushing action and safe on plastics (Applications = 150 approx.)	G5MS-S

4.4.3 Preparation

Item	Precaution
Real-time Clock	This procedure may result in the loss of the real-time clock. Once the treatment is complete, check, and if necessary, re-program the real-time clock and date – see Section 4.4.8, page 31.
Transmitters with Data Loggers	This procedure may result in the loss of logger contents on transmitters fitted with data loggers. To prevent data loss, download logger data before treating the connector pins.

4.4.4 Disconnection

Before DeoxIT treatment, disconnect ALL cables in the following order:

1. Battery pack / power
2. Sensor
3. Pressure transducer (if fitted)
4. Outputs
5. Communications cable (if connected)

Uncap unused connectors.

4.4.5 Order of Treatment

To minimize disruptive effects of repeatedly breaking and making connections perform the following order of treatment using the Stage 1 and Stage 2 processes for each plug and socket in turn:

1. Treat sensor connector and cable (ensure battery is disconnected at this point).
2. Treat battery connector and cable (ensure sensor is disconnected at this point).
3. Treat all other peripheral connections and cables.

4.4.6 Stage 1 – Oxide Removal and Cleaning

To remove existing oxide and clean the pins:

1. Apply a short burst (around 0.5 second duration) of DeoxIT DN5 spray to the metal surfaces of the connectors and to the gold connector pins.




Fig. 4.3 Cleaning the Gold Connector Pins

2. Connect a corresponding male / female connector to the connector under test 5 times.
3. Wait 10 seconds.
4. Reapply one short burst (around 0.5 s duration) of DeoxIT DN5 spray to the metal surfaces.
5. Allow any residue to run out of connector.
6. Wait 30 seconds for the application to dry.

Note. The surfaces may not appear completely dry after this time as a protective layer is left behind when the carrier evaporates.

4.4.7 Stage 2 – Oxide Prevention

To prevent oxide build-up:

1. Apply a very short burst (not more than 0.5 seconds duration) of DeoxIT Gold GN5 spray to the metal surfaces.
Avoid unnecessary spraying onto transmitter housing.
2. Wait 10 seconds.
3. Reapply one very short burst (not more than 0.5 seconds duration) of DeoxIT Gold GN5 spray to the metal surfaces.
4. Allow any residue to run out of connector.
5. Wait 30 seconds for the application to dry.

Note. The surfaces may not appear completely dry after this time as a protective layer is left behind when the carrier evaporates.

4.4.8 Completion tasks

To complete servicing of the plugs and sockets:

1. Reconnect peripheral devices in this order.
 - a. Sensor
 - b. Pressure transducer (if fitted)
 - c. Outputs
 - d. Communications
 - e. Battery pack / power
2. Refit protective caps on unused connection sockets.
3. For transmitters with built-in loggers and no GSM, re-program the real-time clock and date – see Programming Guide (COI/FET2XX–EN).

Important (note)

- It is strongly recommended that the account's factory default authentication password is changed from the factory default on commissioning the flowmeter.
- When changing a password, record it somewhere secure, especially if each flowmeter has a unique password. If a password is lost or unknown, it must be reset to the factory default password using a single-use code that is specific to the applicable meter. This will reset the flowmeter to the factory default settings and allow access to it.

5 Specification

AquaMaster3 transmitter

Mounting

Integral with sensor (integral-mount)

or

Remote up to 200 m (650 ft.)

Housing

IP68 (NEMA 6P), <2 m (6 ft.)

Stainless steel housing in a thermoplastic outer cover with window, encapsulated with polyurethane-based resin.

Electrical connections

IP68 plug and socket, mains cable

Sensor cable

ABB cable supplied as standard

SWA cable available (via adaptor box) on application

Mains supply

85 to 265 V AC @ <3 VA

Connection cable: approx. 3 m (10 ft.)

Mains power failure backup time: Standard, approx. 5 days from internal super capacitor.

Optional, up to 5 years with power cable option AS and external battery option AD.

Renewable power

Solar or wind

Input voltage: 6 to 22 V DC @ <5 W

Note. Renewable energy generators do not operate at maximum capacity, for example, low wind speed, coating of the solar panel, short daylight periods. As a consequence, some installations require generators with a capacity greater than the specified 5 W minimum.

Max. current: 200 mA

Backup power time up to 3 weeks

(dependent on operating conditions)

External battery pack

IP68 (NEMA 6P)

Standard

Manganese alkaline battery pack with nominal 5-year operational life @ 0 to 45 °C (32 to 113 °F) *

Optional

Lithium thionyl chloride 9-cell battery pack with nominal 10-year life *

Lithium thionyl chloride 4-cell battery pack with nominal 5-year life *

Internal battery (integral-mount version only)

IP68 (NEMA 6P) sensor integral housing

Standard

Lithium thionyl chloride 3.6 V D-cell (x 6) with nominal 6-year operational life @ -20 to 60 °C (-4 to 140 °F) *

Suitable batteries, non-solder tag (not supplied):

■ SAFT LS36600 / Varta ER D / Tekcell SB-D02

Battery changeover backup time

Approximately 2 minutes

Pulse and alarm outputs

Three, bidirectional, solid-state switches with common isolation

±35 V DC 50mA

Output 1 – forward only or forward plus reverse pulses

Output 2 – reverse pulses or direction indicator

Output 3 – alarm indicates any problem with measurement or with power

Pulse output – 50 Hz maximum, 50 % nominal duty cycle

Communications options

Serial data communications

Local Port RS232

Note. On battery and renewable energy versions frequent use of the RS232 port considerably reduces battery / standby life.

* Battery life is shorter with GSM, depending on how frequently it is used and for what period. For example, used once per day for SMS automated reporting of data logged at 15 minute intervals, the life of a battery pack would be typically reduced by 5 %. Battery life is shorter at extremes of temperature.

Battery life of the FEV DN200 is 50% of typical life.

Battery life of the WITS GPRS version depends on the configured connection schedule.

Telemetry applications (option)

GSM / SMS modem

Mounting:

Internal

Frequency bands:

Quad band: 850 / 900 / 1800 / 1900 MHz

Functions:

SMS auto report of flow and optionally, pressure logger data (typically 1 s or 1 min. average)

SMS report frequency: typically daily

SMS alarm reporting at time of event, for example power loss, limited to 1 per day

SMS flowmeter configuration

SMS flowmeter diagnosis

SMS total / tariff auto report

WITS / DNP3 version 1.1, 1.2 and 1.3 via TCP/IP GPRS

GSM antenna (option)

Quad band operation:

850 / 900 / 1800 / 1900 MHz

Mounting:

Integral with transmitter or remote.


Antenna environmental:

IP66 (NEMA4) waterproof for accidental submersion

Note. The GSM does not operate with integral antenna under water.

General advice is to mount the antenna as high as possible, always outside of any metal enclosure and not under the surface of the ground.

Temperature ranges



Battery capacity and life are shortened when operating outside the temperature range:

Manganese Alkaline 0 to 45 °C (32 to 113 °F)

Lithium Thionyl Chloride 0 to 60 °C (32 to 140 °F)

Response time (programmable)

Minimum

1 s (mains-powered)

15 s (battery-powered + external renewable energy)

Device languages

English only

Pressure system – external transducer (option)

Pressure range

16 bar Abs.

Connection

Standard quick-fit male probe connector via an adapter cable

Operating temperature range

-20 (ambient) to 70 °C (-4 to 158 °F)

Protect the sample and transducer from freezing.

Accuracy (typical)

±0.4 % of range

Thermal error band (typically 100 °C [212 °F])

±1.5 % span

Cable length

5, 10 or 20 m (16, 33 or 66 ft.)

Logger details (option)

	Logger		
	1	2	3
Logger Function	Flow & Pressure	Flow & Pressure	Forward, Reverse, Tariffs & Net Flow Totals
No. of Records	8831	11361	732
Logging Interval	15 to 65500 s (adjustable)		24 hr (fixed)
Typical Capacity	3 months @15 minutes	7 days (approx.) @ 1 minutes	2 years

	WITS Logger		
	High Speed Sample Data	Archive Log	
Logger Function	Flow & Pressure	Flow & Pressure	Logger Capacity
Logging Interval	60 seconds 90 seconds 180 seconds	15 minutes (configurable)	20.67 days 31 days 62 days

Software availability

Software	Direct RS232	SMS (Text)
ABB AC800M	✗	✓
ABB Generic (for example, LogMaster)	✓	✗
Areal (Topkapi)	✗	✓
MasterVue (I&P AutoChart)	✗	✓
EcoTech	✗	✓
HydroComp	✗	✓
Mobile phone text	✗	✓
OSI PI Database or Capula	✓	✗
QTech	✗	✓
Zeepaard	✗	✓
Agua Ambiente Servicios Integrales SA	✗	✓

DS/FER200/FEF200/FEV200-EN Rev. O

Appendix A – GSM-Equipped Units, Safety Precautions

The following safety precautions must be observed during all phases of the operation, usage, service or repair of this GSM cellular terminal. Failure to comply with these precautions violates safety standards of design, manufacture and intended use of the product. The Company assumes no liability for customer failure to comply with these precautions.

1. When in a hospital or other health care facility, observe the restrictions on the use of mobiles. Switch the cellular terminal or mobile off, if instructed to do so by the guidelines posted in sensitive areas. Medical equipment may be sensitive to RF energy. The operation of cardiac pacemakers, other implanted medical equipment and hearing aids can be affected by interference from cellular terminals or mobiles placed close to the device. If in doubt about potential danger, contact the physician or the manufacturer of the device to verify that the equipment is shielded properly. Pacemaker patients are advised to keep their hand-held mobile away from the pacemaker, while the mobile is on.
2. Switch off the cellular terminal or mobile before boarding an aircraft. Remove the SIM card before shipping. Make sure it cannot be switched on inadvertently. The operation of wireless appliances in an aircraft is forbidden to prevent interference with communications systems. Failure to observe these instructions may lead to the suspension or denial of cellular services to the offender, legal action, or both.
3. Do not operate the cellular terminal or mobile in the presence of flammable gases or fumes. Switch off the cellular terminal when you are near petrol stations, fuel depots, chemical plants or where blasting operations are in progress. Operation of any electrical equipment in potentially explosive atmospheres can constitute a safety hazard.
4. Your cellular terminal or mobile receives and transmits radio frequency energy while switched on. Remember that interference can occur if it is used close to TV sets, radios, computers or inadequately shielded equipment. Follow any special regulations and always switch off the cellular terminal or mobile wherever forbidden when you suspect that it may cause interference or danger.

Note. Cellular terminals or mobiles operate using radio signals and cellular networks cannot be guaranteed to connect in all conditions. Therefore, you should never rely solely upon any wireless device for essential communications, for example emergency calls.

To make or receive calls, the cellular terminal or mobile must be switched on and in a service area with adequate cellular signal strength.

Appendix B Accessories / Spares Kits

B.1 Common accessories

MRBX9969	Close-coupled mounting kit
WEBC2003/10	Remote GSM aerial kit 10 m (32 ft.)
WEBC2110/01 WEBC2110/05 WEBC2110/10	AquaMaster 3 Remote GSM quad band aerial kit: 1m (3.3 ft.) 5m (16.4 ft.) 10m (32 ft.)
B20433 B20434	MIL connector: 4-pin MIL – renewable power connector 7-pin MIL – RS232 connector
WABC2100 WABC2101 WABC2102 MEBX2110 Integral battery type	Batteries / spares Remote battery pack (MnO_2) Remote battery pack ($LiSOCl_2$) – 4 cell Remote battery pack ($LiSOCl_2$) – 9 cell Integral battery carrier assembly (replacement spare) 3.6 V Lithium Thionyl Chloride, size D Recommended manufacturer part numbers: SAFT LS 33600 / Varta ERD / Tekcell SB-D02
WABC2010 WABC2010/01 WABC2010/05 WABC2010/10 WABC2010/20 WABC2010/30 WABC2010/40 WABC2010/50 WABC2010/60 WABC2010/70 WABC2010/80	Sensor cable assembly: 0.5 m (1.6 ft.), for integral / close-coupled 1 m (3.3 ft.), for remote 5 m (16.4 ft.), for remote 10 m (32.8 ft.), for remote 20 m (65.6 ft.), for remote 30 m (98.4 ft.), for remote 40 m (131.2 ft.), for remote 50 m (164.0 ft.), for remote 60 m (196.8 ft.), for remote 70 m (229.6 ft.), for remote 80 m (262.4 ft.), for remote
WABC2010/01 WEBC2011/M WEBC2012/M WEBC2013/M WEBC2014/M WEBC2006/M	Output cable: 1 m (3.3 ft.) wire-ended for Technolog Cello (MIL) for Technolog Cello (Brad Harrision) for RADCOM Multilog for Primayer Xilog 2x19-way MIL
WEBC2024	Connector security plug – pack of 5
WEBC2100	Communication cable: RS232 to USB
WABX2000/05 WABX2000/10	Pressure cable assembly: 16 bar (232 psi), 5 m (16.4 ft.) 16 bar (232 psi), 10 m (32.8 ft.)

B.2 Adapter Cable / Upgrade Kits

WABC2036	Pressure adapter kit: M16 Plastic to MIL
WABC2022/M WABC2023/M	Sensor upgrade kit: M20 Plastic to MIL M20 Armored to MIL
WABC2035 WABC2024/M WABC2025/M WABC2026/M	Sensor adaptor kit: M16 Plastic to MIL M20 Plastic to MIL M20 Armored to MIL ½ in. NPT blanked to MIL

Notes

Acknowledgments

- Capula® is a copyright of Capula Limited 2010.
- EcoTech™ is a registered trademark of EcoTech Pty Ltd.
- HydroComp is a copyright of HydroComp Inc 2010.
- Microsoft Excel™ and Windows™ are registered trademarks of the Microsoft Corp. MeterVue© is a copyright of Information and Performance Services (I&P).
- OSI™ is a registered trademarks of WADIS.
- PMAC™ is a registered trademark of Technolog.
- Primeware™ and Xilog™ are registered trademarks of Primayer.
- QTech™ is a registered trademark of QTech Data Systems Limited.
- Topkapi™ is a registered trademark of AREAL.
- Vodafone PAKNET™ and Vodafone Radiopad™ are registered trademarks of Vodafone.
- Zeepaard is a copyright of Zeepaard Engineering Sdn.Bhd.

Sales



Service



ABB Measurement & Analytics

For your local ABB contact, visit:
www.abb.com/contacts

For more product information, visit:
www.abb.com/measurement

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of ABB.