



ACS850 Template Readme for SREA-01

Handled by

Juho Cederström / Teemu T
Heikkilä

Date

2.2.2009

Pages

1 (1)

DRIVE SETTINGS AND COMPATIBILITY

As of 2.2.2009, the drive software version (1000) supports SREA-01 connection to a single drive by panel port.

In addition, the current drive software version (1000) does not support automatic detection of drives. The drive must be added manually to configuration of SREA-01.

ACS850 is compatible with SREA-01 only with the drive parameter setting

16.16 Menu set active = Long menu (2)

Before adding the drive to SREA-01, the parameter value 16.15 must be changed to value "Load long" either by using the control panel or DriveStudio PC-tool.

INSTALLING THE TEMPLATE

You can install the ACS850 template to SREA-01 by following these steps:

1. Be sure that you have changed the drive parameter 16.16 Menu set active to value Long menu (2). Load long parameter menu by setting parameter 16.15 to Long menu (2).
2. Log in to SREA-01 and go to page Configuration / Templates.
3. Press the upload template button and browse for the uncompressed template files: ACS850_filerevX.Y.xml. Press the upload template button.
4. When you can see ACS850 in the end of the Template list, you are ready to add the drive to device configuration as described in the SREA-01 User's Manual, section Configuration / Devices.

ABB Oy

Postal Address:
Drives
P.O.Box 184
FIN-00381 Helsinki, Finland

Street Address:
Drives
Hiomotie 13
FIN-00380 Helsinki, Finland

Telephone:
+358 10 2211
Telefax:
+358 10 22 xxxxx

Internet:
www.abb.fi
e-mail:
first name.last name
@fi.abb.com

Business Identity Code:
0763403-0
Domicile: Helsinki