

PRODUCT SHEET

# Carlon® non-metallic push-in fittings



## Superior pull-out performance and cost efficiency.

Better than ever, Carlon® non-metallic fittings now available in ½" and ¾" sizes.

### Features and benefits

- Easy push-in installation in knockouts—no tools required
- Certified for one or two cables
- Insertion from inside or outside of enclosures increases installation flexibility
- Snug fit eliminates movement within knockout
- Exceeds pull-out requirements for better cable security
- Distinctive colors to differentiate sizes: 1/2" gray, 3/4" blue
- UL® Listed, CSA Certified




### Installation:



01 Align the flat surface or opening with the burr of the knockout for easier insertion.



02 Installation without cables: Insert the fitting into the knockout from the inside or outside of the enclosure.



03 For two-cable installation: Cables may be inserted individually or together.



Please see product instruction sheet for complete installation instructions and warnings.



### Carlon® non-metallic push-in fittings

Cat. no.	Description	Trade size (in.)	Clamping range (in.)		Suggested application (non-metallic sheathed cable)	Packaging
			min.	max.		
SNM12-6R	Non-metallic fitting ½ in.	½	0.21	0.42	14/2 - 12/2 - 10/2 - 14/3 - 12/3 - 10/3 2 cables: 2 x 14/2 - 2 x 12/2 - 1 x 14/2 - 1 x 12/2	Jar of 50 pcs
SNM12-100CP	Non-metallic fitting ½ in.	½	0.21	0.42	14/2 - 12/2 - 10/2 - 14/3 - 12/3 - 10/3 2 cables: 2 x 14/2 - 2 x 12/2 - 1 x 14/2 - 1 x 12/2	Bag of 100 pcs
SNM34-6R	Non-metallic fitting ¾ in.	¾	0.22	0.65	12/2 - 10/2 - 8/2 - 6/2 - 14/3 - 12/3 - 10/3 - 8/3 - 6/3 2 cables: 2 x 12/2 - 2 x 10/2 - 1 x 12/2 - 1 x 10/2	Jar of 40 pcs
SNM34-100CP	Non-metallic fitting ¾ in.	¾	0.22	0.65	12/2 - 10/2 - 8/2 - 6/2 - 14/3 - 12/3 - 10/3 - 8/3 - 6/3 2 cables: 2 x 12/2 - 2 x 10/2 - 1 x 12/2 - 1 x 10/2	Bag of 100 pcs

### ABB Installation Products

860 Ridge Lake Blvd  
Memphis, TN 38120  
USA

[tnb.abb.com](http://tnb.abb.com)

© Copyright 2018 ABB. All rights reserved.  
Specifications subject to change without notice.



Scan code to learn more.