


	Suoja johdin		MK 6 kevi


Laji	RYHMÄKESKUS		
Tyyppi	RY5E33JS		
Sähkö nro	3310100		
$I_{nA} = 50A$	$U_n = 400V$		
$P_n =$	$P_h =$		
Kotelointi	IP20C	Valm.vuosi	




NRO	NIMITYS	TARKENNUS	A/A	mm ²	N	PE
	Pääkytkin (80 A)					
1F1			B 6A			
1F2			B10A			
1F3			B10A			
2F1			B10A			
2F2			B10A			
2F3			B10A			
3F1			C10A			
3F2			C10A			
3F3			C10A			
4F1			B16A			
4F2			B16A			
4F3			B16A			
5F1			B16A			
5F2			B16A			
5F3			B16A			
10F	Vikavirtasuojakytkin 40A, 30 mA					
10F1			C16A			
10F2			C16A			
10F3			C16A			
11F1			C10A			
11F2			C10A			
11F3			C10A			
12F	Vikavirtasuojakytkin 40A, 30 mA					
12F1			C16A			
12F2			C16A			
12F3			C16A			
13F1			C10A			
13F2			C10A			
13F3			C10A			

KESKUKSEN VARATILAT	
Yhteensä	53 mod

KESKUKSEN MITAT	
Leveys :	550 mm
Korkeus:	800 mm
Syvyys :	112 mm



Yläpääty: 2xC-multilaippa (30x20+2x32)
4x21+2x26mm reikäaihioita
Alapääty: 2xC-multilaippa (30x20+2x32)
4x21+2x26mm reikäaihioita
Syöttö: Alhaalta tai ylhäältä
50mm aihio

Työ nro		Ark. koodi			RY5E33JS-B		KESKUS		RK 1		Työpiir:				
Pvm. 14.10.2014		Suunn. PP		Tark. VN		Hyv. ABB		PÄÄKAAVIO		KOKOONPANOPIIRUSTUS		Loppupiir.			
								Rakennuskohde				Tall.koodi 3310100-K			
												Lehti 01		Lehdestä 02	
												Piirustus nro			